15-213

Machine-Level Programming I: Introduction
Feb. 1, 2000

Topics

- Assembly Programmer's Execution Model
- Accessing Information
  - Registers
  - Memory
- Arithmetic operations

IA32 Processors

Totally Dominate Computer Market

Evolutionary Design

- Starting in 1978 with 8086
- Added more features as time goes on
- Still support old features, although obsolete

Complex Instruction Set Computer (CISC)

- Many different instructions with many different formats
  - But, only small subset encountered with Linux programs
- Hard to match performance of Reduced Instruction Set Computers (RISC)
- But, Intel has done just that!

X86 Evolution: Programmer's View

Name	Date	Transistors
8086	1978	29K

- 16-bit processor. Basis for IBM PC & DOS
- Limited to 1MB address space. DOS only gives you 640K

80286	1982	134K

- Added elaborate, but not very useful, addressing scheme
- Basis for IBM PC-AT and Windows

386	1985	275K

- Extended to 32 bits. Added "flat addressing"
- Capable of running Unix
- Linux/gcc uses no instructions introduced in later models

486	1989	1.9M
Pentium	1993	3.1M

X86 Evolution: Programmer's View

Name	Date	Transistors
Pentium/MMX	1997	4.5M

- Added special collection of instructions for operating on 64-bit vectors of 1, 2, or 4 byte integer data

Pentium II	1997	7M

- Added conditional move instructions
- Big change in underlying microarchitecture

Pentium III	1999	8.2M

- Added "streaming SIMD" instructions for operating on 128-bit vectors of 1, 2, or 4 byte integer or floating point data

Merced	2000?	10M

- Extends to IA64, a 64-bit architecture
- Radically new instruction set designed for high performance
- Will be able to run existing IA32 programs
  - On-board "x86 engine"

Assembly Programmer's View



Programmer-Visible State

- **EIP** **Program Counter**
  - Address of next instruction
- **Register File**
  - Heavily used program data
- **Condition Codes**
  - Store status information about most recent arithmetic operation
  - Used for conditional branching

- **Memory**
  - Byte addressable array
  - Code, user data, (some) OS data
  - Includes stack used to support procedures

Turning C into Object Code

- **Code in files** `p1.c p2.c`
- **Compile with command:** `gcc -O p1.c p2.c -o p`
  - Use optimizations (`-O`)
  - Put resulting binary in file `p`



Compiling Into Assembly

C Code

```
int sum(int x, int y)
{
  int t = x+y;
  return t;
}
```

Generated Assembly

```
_sum:
    pushl %ebp
    movl %esp,%ebp
    movl 12(%ebp),%eax
    addl 8(%ebp),%eax
    movl %ebp,%esp
    popl %ebp
    ret
```

Obtain with command

```
gcc -O -S code.c
```

Produces file `code.s`

Assembly Characteristics

Minimal Data Types

- **"Integer" data of 1, 2, or 4 bytes**
  - Data values
  - Addresses (untyped pointers)
- **Floating point data of 4 or 8 bytes**
- **No aggregate types such as arrays or structures**
  - Just contiguously allocated bytes in memory

Primitive Operations

- **Perform arithmetic function on register or memory data**
- **Transfer data between memory and register**
  - Load data from memory into register
  - Store register data into memory
- **Transfer control**
  - Unconditional jumps to/from procedures
  - Conditional branches

Object Code

Code for `sum`

```
0x401040 <sum>:
    0x55
    0x89
    0xe5
    0x8b
    0x45
    0x0c
    0x03
    0x45
    0x08
    0x89
    0xec
    0x5d
    0xc3
```

- Total of 13 bytes
- Each instruction 1, 2, or 3 bytes
- Starts at address `0x401040`

Assembler

- Translates `.s` into `.o`
- Binary encoding of each instruction
- Nearly-complete image of executable code
- Missing linkages between code in different files

Linker

- Resolves references between files
- Combines with static run-time libraries
  - E.g., code for `malloc`, `printf`
- Some libraries are *dynamically linked*
  - Linking occurs when program begins execution

Machine Instruction Example

```
int t = x+y;
```

```
addl 8(%ebp),%eax
```

Similar to expression `x += y`

```
0x401046:    03 45 08
```

C Code

- Add two signed integers

Assembly

- Add 2 4-byte integers
  - "Long" words in GCC parlance
  - Same instruction whether signed or unsigned
- Operands:
  - `x`: Register `%eax`
  - `y`: Memory `M[%ebp+8]`
  - `t`: Register `%eax`
    - » Return function value in `%eax`

Object Code

- 3-byte instruction
- Stored at address `0x401046`

Disassembling Object Code

Disassembled

```
00401040 <_sum>:
   0:    55              push   %ebp
   1:    89 e5           mov    %esp,%ebp
   3:    8b 45 0c        mov    0xc(%ebp),%eax
   6:    03 45 08        add    0x8(%ebp),%eax
   9:    89 ec           mov    %ebp,%esp
   b:    5d              pop    %ebp
   c:    c3              ret
   d:    8d 76 00        lea    0x0(%esi),%esi
```

Disassembler

`objdump -d p`

- Useful tool for examining object code
- Analyzes bit pattern of series of instructions
- Produces approximate rendition of assembly code
- Can be run on either `a.out` (complete executable) or `.o` file

Alternate Disassembly

Object

```
0x401040:
    0x55
    0x89
    0xe5
    0x8b
    0x45
    0x0c
    0x03
    0x45
    0x08
    0x89
    0xec
    0x5d
    0xc3
```

Disassembled

```
0x401040 <sum>:      push   %ebp
0x401041 <sum+1>:    mov    %esp,%ebp
0x401043 <sum+3>:    mov    0xc(%ebp),%eax
0x401046 <sum+6>:    add    0x8(%ebp),%eax
0x401049 <sum+9>:    mov    %ebp,%esp
0x40104b <sum+11>:   pop    %ebp
0x40104c <sum+12>:   ret
0x40104d <sum+13>:   lea    0x0(%esi),%esi
```

Within gdb Debugger

```
gdb p
diassemble sum
```

- Disassemble procedure

```
x/13b sum
```

- Examine the 13 bytes starting at `sum`

What Can be Disassembled?

```
% objdump -d WINWORD.EXE

WINWORD.EXE:     file format pei-i386

No symbols in "WINWORD.EXE".
Disassembly of section .text:

30001000 <.text>:
30001000:  55              push   %ebp
30001001:  8b ec           mov    %esp,%ebp
30001003:  6a ff           push   $0xffffffff
30001005:  68 90 10 00 30  push   $0x30001090
3000100a:  68 91 dc 4c 30  push   $0x304cdc91
```

- Anything that can be interpreted as executable code
- Disassembler examines bytes and reconstructs assembly source

Moving Data

Moving Data

`movl` *Source,Dest*: Move 4-byte ("long") word

- Accounts for 31% of all instructions in sample

Operand Types

- Immediate: Constant integer data
  - Like C constant, but prefixed with '$'
  - E.g., `$0x400`, `$-533`
  - Encoded with 1, 2, or 4 bytes
- Register: One of 8 integer registers
  - But `%esp` and `%ebp` reserved for special use
  - Others have special uses for particular instructions
- Memory: 4 consecutive bytes of memory
  - Various "address modes"



`movl` Operand Combinations

	Source	Destination		C Analog
movl	*Imm*	*Reg*	`movl $0x4,%eax`	`temp = 0x4;`
		Mem	`movl $-147,(%eax)`	`*p = -147;`
	Reg	*Reg*	`movl %eax,%edx`	`temp2 = temp1;`
		Mem	`movl %eax,(%edx)`	`*p = temp;`
	Mem	*Reg*	`movl (%eax),%edx`	`temp = *p;`

- Cannot do memory-memory transfers with single instruction

Simple Addressing Modes

Normal (R) Mem[Reg[R]]

- Register R specifies memory address

```
movl (%ecx),%eax
```

Displacement D(R) Mem[Reg[R]+D]

- Register R specifies start of memory region
- Constant displacement D specifies offset

```
movl 8(%ebp),%edx
```

Using Simple Addressing Modes

```
void swap(int *xp, int *yp)
{
  int t0 = *xp;
  int t1 = *yp;
  *xp = t1;
  *yp = t0;
}
```

```
swap:
    pushl %ebp              } Set
    movl %esp,%ebp          } Up
    pushl %ebx

    movl 12(%ebp),%ecx      } Body
    movl 8(%ebp),%edx       } Body
    movl (%ecx),%eax        } Body
    movl (%edx),%ebx        } Body
    movl %eax,(%edx)        } Body
    movl %ebx,(%ecx)        } Body

    movl -4(%ebp),%ebx      } Finish
    movl %ebp,%esp          } Finish
    popl %ebp               } Finish
    ret                     } Finish
```


Understanding Swap

```
void swap(int *xp, int *yp)
{
  int t0 = *xp;
  int t1 = *yp;
  *xp = t1;
  *yp = t0;
}
```



Register	Variable
%ecx	yp
%edx	xp
%eax	t1
%ebx	t0

```
movl 12(%ebp),%ecx  # ecx = yp
movl 8(%ebp),%edx   # edx = xp
movl (%ecx),%eax    # eax = *yp (t1)
movl (%edx),%ebx    # ebx = *xp (t0)
movl %eax,(%edx)    # *xp = eax
movl %ebx,(%ecx)    # *yp = ebx
```


Indexed Addressing Modes

Most General Form

D(Rb,Ri,S) **Mem[Reg[Rb]+S*Reg[Ri]+ D]**

- **D:** Constant "displacement" 1, 2, or 4 bytes
- **Rb:** Base register: Any of 8 integer registers
- **Ri:** Index register: Any, except for `%esp`
  - Unlikely you'd use `%ebp`, either
- **S:** Scale: 1, 2, 4, or 8

Special Cases

(Rb,Ri) **Mem[Reg[Rb]+Reg[Ri]]**

D(Rb,Ri) **Mem[Reg[Rb]+Reg[Ri]+D]**

(Rb,Ri,S) **Mem[Reg[Rb]+S*Reg[Ri]]**

Address Computation Instruction

`leal` ***Src,Dest***

- ***Src*** is address mode expression
- Set ***Dest*** to address denoted by expression

Uses

- Computing address without doing memory reference
  - E.g., translation of `p = &x[i];`
- Computing arithmetic expressions of the form x + k*y
  - k = 1, 2, 4, or 8.

Some Arithmetic Operations

Format	Computation	
Two Operand Instructions		
`addl` *Src, Dest*	*Dest* = *Dest* + *Src*	
`subl` *Src, Dest*	*Dest* = *Dest* – *Src*	
`imull` *Src, Dest*	*Dest* = *Dest* * *Src*	
`sall` *Src, Dest*	*Dest* = *Dest* << *Src*	Also called `shll`
`sarl` *Src, Dest*	*Dest* = *Dest* >> *Src*	Arithmetic
`shrl` *Src, Dest*	*Dest* = *Dest* >> *Src*	Logical
`xorl` *Src, Dest*	*Dest* = *Dest* ^ *Src*	
`andl` *Src, Dest*	*Dest* = *Dest* & *Src*	
`orl` *Src, Dest*	*Dest* = *Dest* | *Src*	
One Operand Instructions		
`incl` *Dest*	*Dest* = *Dest* + 1	
`decl` *Dest*	*Dest* = *Dest* – 1	
`negl` *Dest*	*Dest* = – *Dest*	
`notl` *Dest*	*Dest* = ~ *Dest*	

Using `leal` for Arithmetic Expressions

```
int arith
  (int x, int y, int z)
{
  int t1 = x+y;
  int t2 = z+t1;
  int t3 = x+4;
  int t4 = y * 48;
  int t5 = t3 + t4;
  int rval = t2 * t5;
  return rval;
}
```

```
arith:
    pushl %ebp              } Set
    movl %esp,%ebp          } Up

    movl 8(%ebp),%eax       } Body
    movl 12(%ebp),%edx
    leal (%edx,%eax),%ecx
    leal (%edx,%edx,2),%edx
    sall $4,%edx
    addl 16(%ebp),%ecx
    leal 4(%edx,%eax),%eax
    imull %ecx,%eax

    movl %ebp,%esp          } Finish
    popl %ebp
    ret
```


Understanding `arith`

```
int arith
  (int x, int y, int z)
{
  int t1 = x+y;
  int t2 = z+t1;
  int t3 = x+4;
  int t4 = y * 48;
  int t5 = t3 + t4;
  int rval = t2 * t5;
  return rval;
}
```




```
movl 8(%ebp),%eax       # eax = x
movl 12(%ebp),%edx      # edx = y
leal (%edx,%eax),%ecx   # ecx = x+y  (t1)
leal (%edx,%edx,2),%edx # edx = 3*y
sall $4,%edx            # edx = 48*y (t4)
addl 16(%ebp),%ecx      # ecx = z+t1 (t2)
leal 4(%edx,%eax),%eax  # eax = 4+t4+x (t5)
imull %ecx,%eax         # eax = t5*t2 (rval)
```


Another Example

```
int logical(int x, int y)
{
  int t1 = x^y;
  int t2 = t1 >> 17;
  int mask = (1<<13) - 7;
  int rval = t2 & mask;
  return rval;
}
```

```
logical:
    pushl %ebp              } Set
    movl %esp,%ebp          } Up

    movl 8(%ebp),%eax       } Body
    xorl 12(%ebp),%eax
    sarl $17,%eax
    andl $8185,%eax

    movl %ebp,%esp          } Finish
    popl %ebp
    ret
```

$2^{13} = 8192$, $2^{13} - 7 = 8185$

```
movl 8(%ebp),%eax       eax = x
xorl 12(%ebp),%eax      eax = x^y     (t1)
sarl $17,%eax           eax = t1>>17  (t2)
andl $8185,%eax         eax = t2 & 8185
```

CISC Properties

Instruction can reference different operand types
- Immediate, register, memory

Arithmetic operations can read/write memory

Memory reference can involve complex computation
- Rb + S*Ri + D
- Useful for arithmetic expressions, too

Instructions can have varying lengths
- IA32 instructions can range from 1 to 15 bytes

Summary: Abstract Machines

Machine Models	Data	Control
C	1) `char`	1) loops
	2) `int, float`	2) conditionals
	3) `double`	3) `goto`
	4) `struct, array`	4) Proc. call
	5) pointer	5) Proc. return
Assembly	1) byte	3) branch/jump
	2) 4-byte long word	4) `call`
	3) 8-byte quad word	5) `ret`
	4) contiguous byte allocation	
	5) address of initial byte	



Pentium Pro (P6)

History
- Announced in Feb. '95
- Basis for Pentium II & Pentium III

Features
- Dynamically translates instructions to more regular format
  - Very wide, but simple instructions
- Executes operations in parallel
  - Up to 5 at once
- Very deep pipeline
  - 12–18 cycle latency

PentiumPro Block Diagram



Microprocessor Report 2/16/95

PentiumPro Operation

Translates instructions dynamically into "Uops"

- 118 bits wide
- Holds operation, two sources, and destination

Executes Uops with "Out of Order" engine

- Uop executed when
  - Operands available
  - Functional unit available
- Execution controlled by "Reservation Stations"
  - Keeps track of data dependencies between uops
  - Allocates resources

Consequences

- Indirect relationship between IA32 code & what actually gets executed
- Difficult to predict / optimize performance at assembly level

Whose Assembler?

Intel/Microsoft Format

```
lea   eax,[ecx+ecx*2]
sub   esp,8
cmp   dword ptr [ebp-8],0
mov   eax,dword ptr [eax*4+100h]
```

GAS/Gnu Format

```
leal  (%ecx,%ecx,2),%eax
subl  $8,%esp
cmpl  $0,-8(%ebp)
movl  $0x100(,%eax,4),%eax
```

Intel/Microsoft Differs from GAS

- Operands listed in opposite order
  - `mov` Dest, Src
  - `movl` Src, Dest
- Constants not preceded by '$', Denote hexadecimal with 'h' at end
  - `100h`
  - `$0x100`
- Operand size indicated by operands rather than operator suffix
  - `sub`
  - `subl`
- Addressing format shows effective address computation
  - `[eax*4+100h]`
  - `$0x100(,%eax,4)`